



Specifications Osram LED Tube T8 SubstiTUBE  
Advanced (EM/Mains) Standard Output 18.4W  
2300lm - 840 Cool White | 120cm - Replaces 36W

[View Product](#)

## General Information

|                             |                                 |
|-----------------------------|---------------------------------|
| SKU                         | 219863                          |
| EAN                         | 4052899937574                   |
| Brand                       | Osram                           |
| Manufacturer Name           | ST8A-1.2M 18,4W/840 230V EM FS1 |
| Full box quantity           | 25                              |
| Any Lamp all-in warranty    | 5 Years                         |
| Energy efficiency class old | A+                              |
| Average Lifetime (h)        | 50000                           |

## Technical Information

|                             |                 |
|-----------------------------|-----------------|
| Technology                  | LED             |
| Replaces (Watt)             | 36              |
| Wattage                     | 18.4            |
| Dimmable                    | Not Dimmable    |
| Cap / Base                  | G13             |
| Rotatable                   | No              |
| Colour Code                 | 840 Cool White  |
| Colour temperature (Kelvin) | 4000 Cool White |
| Colour Rendering (Ra)       | 80-89           |
| Colour of Light             | White           |

|                      |              |
|----------------------|--------------|
| Light colour options | Single Color |
|----------------------|--------------|

|                       |      |
|-----------------------|------|
| Luminous Flux (Lumen) | 2300 |
|-----------------------|------|

|                          |     |
|--------------------------|-----|
| Luminous Efficacy (lm/W) | 125 |
|--------------------------|-----|

|                       |             |
|-----------------------|-------------|
| Product Type Category | LED Tube T8 |
|-----------------------|-------------|

|                |           |
|----------------|-----------|
| Type of sensor | No Sensor |
|----------------|-----------|

## Lamp Information

|                      |     |
|----------------------|-----|
| LED Starter included | Yes |
|----------------------|-----|

|                  |    |
|------------------|----|
| Requires Ballast | No |
|------------------|----|

|                       |                                                                       |
|-----------------------|-----------------------------------------------------------------------|
| Ballast for LED Tubes | Conventional – there is a starter, Mains – Directly connected to 230V |
|-----------------------|-----------------------------------------------------------------------|

|                 |                 |
|-----------------|-----------------|
| LED Tube Output | Standard Output |
|-----------------|-----------------|

|        |            |
|--------|------------|
| Series | Substitute |
|--------|------------|

## Dimensions

|        |       |
|--------|-------|
| Length | 120cm |
|--------|-------|

|             |      |
|-------------|------|
| Length (mm) | 1200 |
|-------------|------|

|               |    |
|---------------|----|
| Diameter (mm) | 28 |
|---------------|----|

## Why Any-lamp?



Order from the **largest lighting specialist** in Europe



**Customised** quotation



Up to **7 years warranty**



**Easy** return process

